

SIMPLE DERIVATION OF DYADIC GREEN FUNCTIONS OF A SIMPLY MOVING, ISOTROPIC, DIELECTRIC–MAGNETIC MEDIUM

Akhlesh Lakhtakia^{1*} and Tom G. Mackay^{2†}

¹CATMAS — Computational & Theoretical Materials Sciences Group
Department of Engineering Science and Mechanics
Pennsylvania State University
University Park, PA 16802–6812, USA

²School of Mathematics
University of Edinburgh
Edinburgh EH9 3JZ
United Kingdom

ABSTRACT: Dyadic Green functions for time–harmonic fields in a homogeneous, isotropic, dielectric–magnetic medium, moving with constant velocity, are derived by first implementing a simple transformation and then using the dyadic Green functions available for uniaxial dielectric–magnetic mediums.

Keywords: *Dyadic Green functions, Minkowski constitutive relations, Uniaxial medium*

*Corresponding author. E–mail: akhlesh@psu.edu

†E–mail: T.Mackay@ed.ac.uk

A significant portion of the electromagnetics literature is devoted to wave propagation in simply moving, homogeneous, isotropic, dielectric-magnetic mediums [1]. The dyadic Green functions (DGFs) of such a medium (with respect to an observer in an inertial non-co-moving frame of reference) have therefore been derived, and are available in closed form [2]. We present here an alternative — and simple — derivation of these DGFs by first implementing a straightforward transformation and then using the DGFs available for uniaxial dielectric-magnetic mediums.

From the perspective of a co-moving observer, let the frequency-domain constitutive properties of a medium be characterized by its relative permittivity ϵ_r and relative permeability μ_r . Suppose next that this medium is moving with constant velocity $\mathbf{v}$ with respect to another inertial observer; then, the Minkowski constitutive relations of this medium may be stated as follows [2]:

$$\mathbf{D} = \epsilon_0 \epsilon_r \underline{\underline{\alpha}} \cdot \mathbf{E} + c_0^{-1} \mathbf{m} \times \mathbf{H}, \quad (1)$$

$$\mathbf{B} = -c_0^{-1} \mathbf{m} \times \mathbf{E} + \mu_0 \mu_r \underline{\underline{\alpha}} \cdot \mathbf{H}. \quad (2)$$

Here and hereafter,

$$\mathbf{v} = v \hat{\mathbf{v}}, \quad (3)$$

$$\underline{\underline{\alpha}} = \alpha \underline{\underline{I}} + (1 - \alpha) \hat{\mathbf{v}} \hat{\mathbf{v}}, \quad (4)$$

$$\alpha = \frac{1 - \beta^2}{1 - \epsilon_r \mu_r \beta^2}, \quad (5)$$

$$\mathbf{m} = m \hat{\mathbf{v}}, \quad (6)$$

$$m = \beta \frac{\epsilon_r \mu_r - 1}{1 - \epsilon_r \mu_r \beta^2}, \quad (7)$$

$$\beta = v/c_0, \quad (8)$$

and $c_0 = 1/\sqrt{\epsilon_0 \mu_0}$ is the speed of light in free space (i.e., vacuum).

The frequency-domain Maxwell curl postulates in the chosen medium (with respect to the non-co-moving observer) may be set down as

$$\nabla \times \mathbf{E}(\mathbf{r}) = i\omega [\mu_0 \mu_r \underline{\underline{\alpha}} \cdot \mathbf{H}(\mathbf{r}) - c_0^{-1} \mathbf{m} \times \mathbf{E}(\mathbf{r})], \quad (9)$$

$$\nabla \times \mathbf{H}(\mathbf{r}) = -i\omega [\epsilon_0 \epsilon_r \underline{\underline{\alpha}} \cdot \mathbf{E}(\mathbf{r}) + c_0^{-1} \mathbf{m} \times \mathbf{H}(\mathbf{r})] + \mathbf{J}(\mathbf{r}), \quad (10)$$

where the phasor $\mathbf{J}(\mathbf{r})$ represents the source electric current density. Our objective is to find the DGFs $\underline{\underline{G}}_e(\mathbf{r}, \mathbf{s})$ and $\underline{\underline{G}}_m(\mathbf{r}, \mathbf{s})$ such that

$$\mathbf{E}(\mathbf{r}) = i\omega \mu_0 \int \int \int \underline{\underline{G}}_e(\mathbf{r}, \mathbf{s}) \cdot \mathbf{J}(\mathbf{s}) d^3 \mathbf{s}, \quad (11)$$

$$\mathbf{H}(\mathbf{r}) = \int \int \int \underline{\underline{G}}_m(\mathbf{r}, \mathbf{s}) \cdot \mathbf{J}(\mathbf{s}) d^3 \mathbf{s}, \quad (12)$$

with the integrations being carried out over the region where $\mathbf{J}(\mathbf{r})$ is nonzero.

We begin by using a transformation provided by Lakhtakia & Weiglhofer [3]; thus, we define transformed field and source phasors as

$$\mathbf{e}(\mathbf{r}) = \mathbf{E}(\mathbf{r}) \exp(ik_0 \mathbf{m} \cdot \mathbf{r}), \quad (13)$$

$$\mathbf{h}(\mathbf{r}) = \mathbf{H}(\mathbf{r}) \exp(ik_0 \mathbf{m} \cdot \mathbf{r}), \quad (14)$$

$$\mathbf{j}(\mathbf{r}) = \mathbf{J}(\mathbf{r}) \exp(ik_0 \mathbf{m} \cdot \mathbf{r}), \quad (15)$$

where $k_0 = \omega\sqrt{\epsilon_0\mu_0}$ is the free-space wavenumber. Hence, (9) and (10) respectively transform to

$$\nabla \times \mathbf{e}(\mathbf{r}) = i\omega\mu_0\mu_r \underline{\underline{\alpha}} \cdot \mathbf{h}(\mathbf{r}), \quad (16)$$

$$\nabla \times \mathbf{h}(\mathbf{r}) = -i\omega\epsilon_0\epsilon_r \underline{\underline{\alpha}} \cdot \mathbf{e}(\mathbf{r}) + \mathbf{j}(\mathbf{r}). \quad (17)$$

The solutions of (16) and (17) may be written as

$$\mathbf{e}(\mathbf{r}) = i\omega\mu_0 \int \int \int \underline{\underline{g}}_e(\mathbf{r}, \mathbf{s}) \cdot \mathbf{j}(\mathbf{s}) d^3\mathbf{s}, \quad (18)$$

$$\mathbf{h}(\mathbf{r}) = \int \int \int \underline{\underline{g}}_m(\mathbf{r}, \mathbf{s}) \cdot \mathbf{j}(\mathbf{s}) d^3\mathbf{s}, \quad (19)$$

The DGFs appearing in these solutions are for a dielectric-magnetic medium with a distinguished axis, and are available as [4]

$$\underline{\underline{g}}_e(\mathbf{r}, \mathbf{s}) = \mu_r \alpha \left(\underline{\underline{\alpha}}^{-1} + \frac{\nabla \nabla}{k_v^2} \right) \frac{\exp(ik_v R_v)}{4\pi R_v}, \quad (20)$$

$$\underline{\underline{g}}_m(\mathbf{r}, \mathbf{s}) = \epsilon_r \alpha \underline{\underline{\alpha}}^{-1} \times \nabla \frac{\exp(ik_v R_v)}{4\pi R_v}, \quad (21)$$

where

$$k_v = k_0 \alpha \sqrt{\epsilon_r \mu_r}, \quad (22)$$

$$R_v = \sqrt{(\mathbf{r} - \mathbf{s}) \cdot \underline{\underline{\alpha}}^{-1} \cdot (\mathbf{r} - \mathbf{s})}. \quad (23)$$

Reversing the transformation (13)–(15), we find the sought-after DGFs as follows:

$$\begin{aligned} \underline{\underline{G}}_e(\mathbf{r}, \mathbf{s}) &= \mu_r \alpha \exp[-ik_0 \mathbf{m} \cdot (\mathbf{r} - \mathbf{s})] \\ &\quad \left(\underline{\underline{\alpha}}^{-1} + \frac{\nabla \nabla}{k_v^2} \right) \frac{\exp(ik_v R_v)}{4\pi R_v}, \end{aligned} \quad (24)$$

$$\begin{aligned} \underline{\underline{G}}_m(\mathbf{r}, \mathbf{s}) &= \epsilon_r \alpha \exp[-ik_0 \mathbf{m} \cdot (\mathbf{r} - \mathbf{s})] \\ &\quad \underline{\underline{\alpha}}^{-1} \times \nabla \frac{\exp(ik_v R_v)}{4\pi R_v}. \end{aligned} \quad (25)$$

These expressions can be put in the same form as the DGFs provided in Chen's textbook [2, Chap 11].

References

- [1] J. Van Bladel, *Relativity and engineering*, Springer, Berlin, 1984.
- [2] H.C. Chen, *Theory of electromagnetic waves*, McGraw-Hill, New York, 1983.
- [3] A. Lakhtakia and W.S. Weiglhofer, On electromagnetic fields in a linear medium with gyrotropic-like magnetoelectric properties, *Microwave Opt Technol Lett* 15 (1997) 168–170.
- [4] A. Lakhtakia, V.V. Varadan and V.K. Varadan, Time-harmonic and time-dependent dyadic Green's functions for some uniaxial gyroelectromagnetic media, *Appl Opt* 28 (1989) 1049–1052.